

# F1-110(G)

## TECHNICAL SPECIFICATION

ITEM	DESCRIPTION																		
<b>VIDEO</b>																			
Input Channel	2 CHANNEL																		
Input impedance	75 ohm Unbalanced																		
Input Format	PAL/NTSC (Auto Detection), Composite																		
Maximum Input	1.0Vp-p @ 75 Ohm Unbalanced																		
Output Channel	1 Ch.(PIP Support)																		
Output impedance	75 ohm Unbalanced																		
Output Format	PAL/NTSC (according to Input), Composite																		
Maximum Output	1.0Vp-p @ 75 Ohm Unbalanced																		
Deinterlace	Perform high quality deinterlacing for arbitrary format of interlaced video input																		
<b>RECORDING</b>																			
Encoding	H.264																		
File Format	SFR (Proprietary Format)																		
Video Recording Resolution	<table border="1"> <thead> <tr> <th>Format</th> <th>PAL</th> <th>NTSC</th> </tr> </thead> <tbody> <tr> <td>4CIF</td> <td>704x576</td> <td>704x480</td> </tr> <tr> <td>CIF</td> <td>352x288</td> <td>352x240</td> </tr> </tbody> </table>	Format	PAL	NTSC	4CIF	704x576	704x480	CIF	352x288	352x240									
Format	PAL	NTSC																	
4CIF	704x576	704x480																	
CIF	352x288	352x240																	
Video Recording Quality	<table border="1"> <thead> <tr> <th>Quality</th> <th>Highest</th> <th>High</th> <th>Normal</th> <th>Low</th> <th>Lowest</th> </tr> </thead> <tbody> <tr> <td>4CIF (kbps)</td> <td>1700</td> <td>1700</td> <td>1500</td> <td>1200</td> <td>1100</td> </tr> <tr> <td>CIF (kbps)</td> <td>1400</td> <td>1400</td> <td>1100</td> <td>900</td> <td>650</td> </tr> </tbody> </table>	Quality	Highest	High	Normal	Low	Lowest	4CIF (kbps)	1700	1700	1500	1200	1100	CIF (kbps)	1400	1400	1100	900	650
Quality	Highest	High	Normal	Low	Lowest														
4CIF (kbps)	1700	1700	1500	1200	1100														
CIF (kbps)	1400	1400	1100	900	650														
Video Recording Frame Rate	<table border="1"> <tbody> <tr> <td>NTSC</td> <td>30/10, 15/15, 10/10, 3/3, 1/1 fps</td> </tr> <tr> <td>PAL</td> <td>25/8, 12/12, 8/8, 3/3, 1/1 fps</td> </tr> </tbody> </table>	NTSC	30/10, 15/15, 10/10, 3/3, 1/1 fps	PAL	25/8, 12/12, 8/8, 3/3, 1/1 fps														
NTSC	30/10, 15/15, 10/10, 3/3, 1/1 fps																		
PAL	25/8, 12/12, 8/8, 3/3, 1/1 fps																		
Recording MODE	Continuous Recording / Emergency / Schedule / Alarm / Shock-Sensor																		
Decoding Video Format	As recorded Quality & Frame Rate																		
Pre-recording Time	Max. 5sec@Normal Mode Recording																		
Storage	Support SD, SDHC(2~32GB, More than Class4 )																		
Storage File System	FAT16, FAT32(recommended)																		
Allocation Unit Size`	32Kbytes(recommended) @2GB-32GB SD/SDHC																		
Maximum Recording File	5,000 files																		

## AUDIO

<b>Compression Format</b>	8KHz, 16bit Mono PCM
<b>Input Channel</b>	2 Ch. Mono
<b>Input impedance</b>	4.7K ohm typ.
<b>Maximum Input</b>	1.2 Vp_p @ Audio Input Level 1(Menu)
<b>Output Channel</b>	1 Ch. Mono, Unbalanced
<b>Maximum Output</b>	13mW@RL =16ohm, Unbalanced

## ALARM

<b>Input</b>	4 Ch. TTL(Internal pull-up), 40V max.
<b>Output</b>	1 Ch. TTL(Open Drain), 15V max. 500mA max.

## OPERATING MODE

<b>Operating Mode</b>	Normal Mode: Live/Playback/Menu/Search/Record Parking Mode: Record Only
-----------------------	--

## VIEWER SOFTWARE

<b>Monitoring Environment</b>	Client S/W
<b>File Convert</b>	AVI(Audio video interleaving)

## I/O

<b>I/O</b>	28pin Pluggable Header Connector (Video out 1CH, MIC in 2CH, Speaker out 1CH, Alarm in 4CH, Alarm out 1CH, RS485, Emergency REC, Power Control)
<b>Camera</b>	8pin Pluggable Header Connector (Video input 2CH, Camera power output 2CH)
<b>Power</b>	4pin Pluggable Header Connector (DC input, Battery input)
<b>SD Slot</b>	1Port, SD Card Slot

## OTHERS

<b>LED</b>	4 Status LED (Power, REC, Fault, GPS)
<b>Remote Control</b>	1 IR Receiver
<b>Shock Sensor</b>	3-Axis Shock Detection

## POWER

<b>Input Voltage Range</b>	Main(DC): 10 to 15VDC(@9.5VDC Cut off) Battery: 12 to 15VDC (@12VDC Cut off)
<b>Power Consumption</b>	Normal Mode: Approx. 300mA @ 12VDC (750mA max. initial peak current @ 12VDC ) Standby Status on Parking Mode: Approx. 6mA @ 12VDC Input power bypass @ 10 to 15VDC, 900mA max.
<b>Camera Power Output</b>	Power is supplied to camera only on normal and wakeup mode. ※ Caution: Be sure to check camera input voltage range(before connection)

## ENVIRONMENTAL

**Operating Temperature** -20 ~ +60 °C

**Humidity** 30 ~ 80 %RH (non-condensing)

## PHYSICAL

**Dimension** 120(W) x 78(L) x 29.5(H) mm

**Weight** Approx.205g

## ACCESSORY

**Remote Control** Supplied

**SD Memory Card** Option

**GPS Antenna** F1-110G Model Only

**I/O Wire Harness** Supplied(Receptacle to wire)

**Camera Wire Harness** Supplied(Receptacle to wire)

**Power Wire Harness** Supplied(Receptacle to wire)